

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets

(11) Publication number:

0 025 292
A1

(12)

EUROPEAN PATENT APPLICATION

(21) Application number: 80302849.7

(51) Int. Cl.³: H 02 K 3/51

(22) Date of filing: 18.08.80

(30) Priority: 31.08.79 US 71632

(43) Date of publication of application:
18.03.81 Bulletin 81/11(84) Designated Contracting States:
BE CH DE FR GB IT LI(71) Applicant: WESTINGHOUSE ELECTRIC CORPORATION
Westinghouse Building Gateway Center
Pittsburgh Pennsylvania 15222(US)(72) Inventor: Flick, Carl
5618 Darlington Road
Pittsburgh Pennsylvania 15217(US)(74) Representative: van Berlyn, Ronald
23 Centre Heights
London NW3 6JG(GB)

(54) Dynamoelectric machine having enhanced unbalanced stator current capability.

(57) Surface currents are induced in dynamoelectric machine rotor body portions by negative sequence currents during unbalanced load operation, which are shunted away from retaining rings situated on opposite axial ends of the rotor. The retaining rings (28) are shrink fitted on both ends of the rotor's body portion and extend in both axial directions. Shunting the rotor surface currents away from the retaining rings (28) provides an operating temperature therein of sufficiently low level to maintain high electrical joint integrity between the retaining ring and rotor. A mantle (38) of highly conductive material surrounds both retaining rings electrically connected to the rotor body. Wedges (34) constitute electrically conductive material and provide longitudinal electrical conductor retention in the rotor slots.

EP 0 025 292 A1

./...




FIG. 3

1

DYNAMOELECTRIC MACHINE HAVING ENHANCED
UNBALANCED STATOR CURRENT CAPABILITY

This invention relates to dynamoelectric machines, and specifically to rotor structures of dynamoelectric machines, such as turbine generators, and in particular, to means for shunting currents induced in
5 rotor surfaces by externally applied magnetic fields away from retaining rings situated at both ends of the rotor.

Generator rotors according to prior art include shaft and body portions of relatively small and large diameter, respectively. Longitudinal slots usually extend
10 axially along the outer periphery of the rotor body. Longitudinal electrical conductor portions disposed in different rotor slots are normally interconnected at each axial end of the rotor body by end turn electrical conductor portions. The longitudinal conductor portions are
15 radially restrained by wedges inserted in those slots radially outside the longitudinal electrical conductors. The end turn portions, on the other hand, are radially restrained during high speed rotor rotation by retaining ring structures which usually constitute high strength
20 cylindrical members which are normally affixed to the rotor body's outer periphery through a shrink fitting process. Since the end turn portions lie radially beneath the retaining rings, centrifugal forces exerted on those end turn portions during rotor rotation are counteracted
25 by internal forces in the retaining rings.

During normal service, central station turbine generators operate with substantially balanced polyphase (commonly three phase) loads. Generator operation is, however, sometimes required for unbalanced load whose duration may be continuous or short. An example of the latter is an unbalanced fault typically occurring as a line-to-line short circuit. During unbalanced load operation or unbalanced fault occurrence, stator windings of turbine generators or other dynamoelectric machines carry a system of currents, denoted in technical parlance as a negative-sequence system, which generates magnetomotive forces that rotate at the generator's synchronous speed in a direction opposite that of rotor rotation. Such magnetomotive forces induce currents in the conducting paths of the rotor (primarily at the surface) and at twice the line frequency. For example, such rotor induced currents for a 60 hertz generator have a frequency of 120 hertz. Analyzing the paths in which these induced surface currents flow in the complexly shaped, discontinuous rotor structure is a difficult task and has been the subject of much design effort.

The induced rotor surface currents travel in a substantially axial direction and eventually enter the rotor's retaining rings. High strength alloys which are customarily utilized for retaining rings usually have relatively high electrical resistance which causes substantial I^2R heating losses. Additionally, since each retaining ring is normally joined (typically shrunk on) to the rotor body in its restraining configuration, heating losses therein tend to expand the retaining ring and reduce the shrink fit pressure between it and the rotor body. As such, the electrical connection between the retaining ring and the rotor body develops a higher resistance which leads to higher heating losses and further aggravates the undesirable situation. For a given load unbalance or fault, dynamoelectric machines of higher rating will usually sustain higher heating losses in the

retaining rings and induce greater thermal expansion thereof.

Previous attempts by machine designers to minimize current flow in the retaining rings include the use of end amortisseur connecting bars or rings which are highly conductive damper members operationally disposed radially inside the retaining rings and radially outside the end turn portions. Use of such highly conductive dampers was thought to shunt the induced rotor surface currents away from the retaining rings and thus reduce their heating and minimize disadvantages resulting therefrom. However, recent studies indicate that use of such radially inner dampers may provide very little relief from the I^2R heating affects of the induced rotor surface current on the retaining rings. Additional attempts to shield the retaining rings from induced rotor surface currents include this disclosure in the specification of U.S. Patent No. 3,324,324. Such structure shows insulation being interposed between the retaining rings and current carrying portions of the rotor body. Such structure, while reducing retaining ring heating, shunts the rotor surface current to other paths which are also vulnerable to overheating.

According to the present invention, a dynamo-electric machine, comprises a cylindrical rotor body portion having a plurality of longitudinal slots disposed in its outer surface, an electrical winding cooperatively associated with the rotor body, said winding comprising a plurality of conductors, said conductors including longitudinal portions disposed in said rotor slots and end turn portions connecting said longitudinal portions at both axial ends of the rotor body, said end turn portions extending axially beyond the rotor body a retaining ring structure joined to each axial end of said rotor body, said retaining ring structure being disposed about the conductor end turn portions to restrain radially outward movement thereof during rotor rotation two highly conduc-

tive mantle structures each having an inner surface and an outer surface, said mantle structures being disposed about each of the retaining ring structures such that said inner surface is in intimate electrical contact with said retaining ring, and means for electrically connecting said mantle structure to said rotor surface, said electrical connecting means providing an electrical path separate from said retaining ring structure.

Conveniently, the machine includes a cylindrical rotor body which has a plurality of longitudinal slots, an electrical winding including longitudinal portions and end turn portions which are respectively situated within the slots and at both axial ends of the rotor, a cylindrical retaining ring structure joined to each axial end of the rotor body in surrounding relationship with the end turn portions, a highly conductive mantle structure joined in intimate electrical contact with the radially outer surface of each retaining ring structure, and means in electrical parallel relationship with the retaining ring structure for electrically connecting the mantle structure and the rotor body's surface. The mantle structure's radial thickness has a preferable minimum of about one depth of penetration or skin thickness of electrical current penetration for electrical current induced on the rotor surface. The depth of penetration or skin thickness is a function of the induced rotor current's frequency and the mantle structure's material properties. The mantle thickness required to effectively shunt the rotor induced current away from the retaining rings increases for decreasing current frequency and decreasing mantle conductivity. The preferable minimum mantle radial thickness for a given material corresponds approximately to the skin thickness for the lowest common frequency (120 Hertz) for rotor surface induced currents, but smaller mantle thicknesses down to a minimum of about one-half skin thickness are effective in substantially reducing heating losses in the underlying retaining ring.

The electrical connection means in a preferred embodiment of the invention constitutes electrically conductive wedges which are receivable in the longitudinal slots radially outside the longitudinal conductor portions and have radial extensions which are contactable, along a radially outer surface thereof, with the mantle structures. To provide an optimum electrical connection between the wedges' radial extension's outer surfaces and the mantle structures a thin connecting member is disposable in intimate contact with the two joinable components. The thin, connecting member preferably constitutes a softer material of higher conductivity than the wedges or the mantle so as to accommodate any local asperities, which would otherwise limit the contact area and increase electrical contact resistance. An interference fit between the mantle's radial inner surface and the wedges' radial extensions' outer surfaces facilitates assembly and simplifies component fabrication. A cylindrical support member is preferably situated radially outside each mantle structure so as to maintain the mantle structure's integrity during high speed rotor rotation. For conductive cylindrical support members their radial thicknesses are preferably less than one depth of electrical current penetration for rotor surface induced current.

Use of highly conductive mantle structures and support members whose preferable respective thicknesses are approximately as great as and less than one skin thickness of electrical current penetration permits electrical current carrying domination of the mantle structures over that of the retaining ring structures. As such, the relatively lower electrically resistant mantle structures electrically shield the retaining rings, incur lower I^2R heating losses, and avoid unfavorable consequences resulting from thermal expansion of the retaining rings.

The invention will now be described, by way of example, with reference to the following detailed description, taken in connection with the accompanying drawings in which:

5 Figure 1 is a transverse partial sectional view of a prior art exemplary turbine generator;

 Figure 2 is a partial transverse sectional view of the present invention;

10 Figure 3 is a transverse sectional view of one end of the rotor illustrated in Figure 2; and

 Figure 4 is a transverse sectional view of an alternate embodiment to that illustrated in Figure 3.

 The present invention is concerned primarily with improved restraining means for conductor end turn
15 portions disposed at both axial ends of dynamoelectric machine rotors. Accordingly, in the description which follows the invention is shown embodied in a large turbine generator. It should be understood, however, that the invention may be utilized as a conductor end turn portion
20 restraining means in any dynamoelectric machine.

 Figure 1 is a partial transverse sectional view of a prior art exemplary turbine generator 10. While generator 10 is illustrated as being of gas cooled rotor construction, machines of multiphase capability having
25 liquidly cooled rotors could utilize the present invention with equal facility.

 Generator 10 includes an outer gas tight casing 12 which, in this case, is filled with a coolant gas normally constituting hydrogen. Generator 10 has a laminated stator core 14 of usual construction which is supported within casing 12 in any suitable manner. Stator core
30 14 is provided with longitudinal slots which receive high voltage stator winding coils 16. Stator winding coils 16 are suitably interconnected at both axial ends of stator
35 14 in end turn regions 18 to provide multiphase (normally three) operation.

Rotor structure 20 is suitably journaled and supported in casing 12 so as to be rotatable relative to stator core 14. Rotor structure 20 includes reduced diameter shaft portion 22 and conductor carrying rotor body portion 24. Field winding coils are disposed on rotor body portion 24 in such manner as to provide any suitable number of poles. Field winding coils constitute longitudinal portions 25 and end turn portions 26 which are respectively disposed in longitudinal slots 27 and end turn regions 18. The longitudinal conductor portions are radially restrained within slots 27 by slot wedges 29 which are cooperatively configured with slots 27 to prevent radial expulsion of wedges 29 therefrom during high speed rotor rotation and thus obstruct expulsion of the longitudinal winding portions 25 situated radially thereunder. The end turn portions 26 of the field winding extend axially beyond both axial ends of rotor body portion 24 into end turn regions 18 and electrically interconnect the longitudinal, slot-disposed portions 25 of the field winding.

Retaining ring structure 28 as shown in Fig. 1 is affixed to the end of rotor body 24 and is in radially restraining relationship with the field winding's end turn portions 26 to prevent radially outward movement thereof during high speed rotor rotation. Retaining ring end plate 30 augments the structural rigidity of retaining ring structure 28 so as to maintain the cylindrical shape thereof and axially restrain the end turn portions 26 adjacent rotor body 24. While only one axial end of rotor structure 20 has been illustrated and discussed, it is to be understood that for purposes of the present invention, the other axial end of rotor body portion 24 utilizes components 28 and 30 (retaining ring and retaining ring end plate respectively) for the same purposes.

During unbalanced load or fault operation, stator winding coils 16 carry a negative sequence system of currents which induce surface currents in conducting

paths on the rotor body portion 24. Since retaining ring structure 28 is joined to rotor body portion 24, it carries the aforementioned surface current induced in rotor body portion 24. Since the retaining ring structure 28 is typically made of high strength, high resistivity, non-magnetic alloy steel, I^2R heating losses from those induced currents flowing therethrough can become substantial. Such heating losses can cause thermal expansion of retaining ring structure 28 and reduce the electrical contact pressure between retaining ring structure 28 and rotor body portion 24. Such reduced electrical contact pressure causes increased resistance and increased thermal expansion of retaining ring structure 28 so as to further deteriorate the electrical integrity, increase the heating losses, and aggravate the already unfavorable current flow induced relationship between retaining ring structure 28 and rotor body 24.

Figure 2 is a partial transverse sectional view of a turbine generator in which an improved conductor end turn restraining structure is provided. An enlarged illustration of the rotor body portion 24 and associated structure for restraining the end turn portions 26 of the field winding of Figure 2 is shown in Figure 3. The structure exemplified in Figure 3 radially restrains the end turn portions 26 of the field winding and minimizes the heating losses normally occurring in the prior art's retaining ring. It should be understood that while eight end turn portions 26 which each preferably include hollow conductors for efficient internal cooling are illustrated, any suitable number of end turn portions may be utilized. The end turn portions 26 are electrically insulated from retaining ring structure 28 by insulation layer 32. Retaining ring structure 28, shown disposed in operating position, axially abutts and circumferentially surrounds the rotor body portion 24 and a longitudinal slot wedge structure 34. Although only a single longitudinal wedge structure 34 is shown, it is to be understood that the

retaining ring structure 28 axially abutts and circumferentially surrounds a plurality of circumferentially separated wedge structures 34 in Figure 2. Fitted insulating blocks 36 separate and maintain a fixed spatial relationship between the end turn portions 26 of the field winding.

Mantle 38, disposed radially about retaining ring structure 28 and end ring 30, constitutes highly conductive material whose preferable thickness is approximately one depth of electrical current penetration at the rotor induced surface current frequency (commonly 120 hertz) or more. Such thickness is, by example, approximately .25 inches for copper or .44 inches for aluminum alloys whose respective conductivities are 100% and 30% as determined by the International Annealed Copper Standard. Mantle 38 is preferably placed in intimate electrical contact with retaining ring structure 28 by roll forming or other suitable joining process. A relatively highly conductive material surrounding a relatively highly resistive material can be shown to be electrically dominant over and effectively shield the resistive material if the conductive material thickness is approximately one electrical skin depth. Mantle thicknesses less than the preferable one skin depth substantially reduce retaining ring structure 28's heating losses down to a preferable minimum thickness of one-half skin depth. Since rotor induced surface currents lie primarily within one skin thickness of the radially outer surface, highly conductive mantle 38 readily conducts those currents with minimal I^2R heating losses. Radial extension portion 40 of slot wedge structure 34 preferably electrically contacts mantle 38 along outer surface 41 in an electrically parallel relation to its contact with retaining ring 28.

A thin sheet of extremely high conductivity material 42 such as silver is preferably placed at the interface between mantle 38 and outer, engagement surface 41. Thin sheet 42 is preferably brazed to mantle 38 prior

to its roll formation with retaining ring structure 28 and is preferably softer than mantle 38 and radial extension's outer surface 41 so as to permit an interference (normally of shrink fit character) fit therebetween of low electrical resistivity and easy formation.

Support member 44 is preferably disposed in intimate contact with and radially about mantle 38 so as to provide rigid support therefor during high speed rotor rotation. Support member 44 preferably comprises a high strength, high resistivity, non-magnetic alloy such as that known in the trade as ASTM-289 steel or Inconel 718. Support member 44 provides structural strength for mantle 38 since high conductivity materials are often relatively low in mechanical properties. Key 46 is circumferentially disposed about the rotor body portion 24 and longitudinal slot wedge structures 34 and lies radially within retaining ring structure 28. Key 46, when disposed in the illustrated operating position, locks the retaining ring structure 28, longitudinal slot wedges 34, and rotor body portion 24 in a fixed relationship.

When a substantially composite structure such as the intimately joined support member mantle includes a relatively highly resistive material surrounding a highly conductive material, it can be shown that the conductive material will electrically dominate and reduce electrical losses in the overlying resistive material if the resistive material's thickness is less than one electrical skin depth. It is to be understood that the conductive material will increasingly dominate the resistive material as the resistive material's thickness is decreased. For the present application support member 44 (constituting resistive material) should have a thickness no greater than required from structural support considerations. By example, support member 44 has a preferable radial thickness of less than one half skin depth of induced current penetration so as to permit copper mantle 38's electrical conductivity characteristics to dominate that of support

member 44. Such domination compels most current to enter mantle 38 and result in little I^2R heating losses in and thermal expansion of retaining ring structure 28 and support member 44. A typical thickness of such previously mentioned alloys of high strength, high resistivity, non-magnetic material used in support member 44 is about .5 inches with the depth of electrical current penetration or skin thickness being approximately 1.5 inches. An alternative to such high strength alloys in support member 44 includes a high strength fiber-reinforced resin such as carbon fiber in an epoxy matrix. Such materials could advantageously be formed and cured in place rather than being installed over and typically shrunk for the case where the support member constitutes an alloy.

Figure 4 illustrates an alternate embodiment of the conductive longitudinal slot wedge structure 34. The alternate wedge structure 34' has a radial extension portion 40' which includes a radially outer surface 41' of greater axial extent and area than the radial extension outer surface 41. Such increased contact between mantle 38 and conductive longitudinal slot wedge structure 34' can provide an electrical connection therebetween of lower resistivity than that illustrated in Figure 3.

Mantle component 38 and support member component 44 preferably protrude radially inwardly at the outboard axial ends (one end is shown in Figures 3 and 4) of retaining ring structure 28 and end plate 30 to provide more effective electrical shielding and restrict relative axial movement among those components, retaining ring structure 28, and end plate 30.

It will now be apparent that an improved dynamo-electric machine has been provided in which a highly conductive mantle is circumferentially disposed about and in intimate contact with the retaining rings. Such relative disposition enables mantle 38 to affectively shield the retaining ring 28 from electrical currents induced in the rotor body surface. Such shielding allows the utiliz-

ing, multiphase dynamoelectric machine tolerate, to a greater extent, the effects of unbalance loads or faults.

What we claim is:

1. A dynamoelectric machine comprising a cylindrical rotor body portion having a plurality of longitudinal slots disposed in its outer surface, an electrical winding cooperatively associated with the rotor body, said winding comprising a plurality of conductors, said conductors including longitudinal portions disposed in said rotor slots and end turn portions connecting said longitudinal portions at both axial ends of the rotor body, said end turn portions extending axially beyond the rotor body a retaining ring structure joined to each axial end of said rotor body, said retaining ring structure being disposed about the conductor end turn portions to restrain radially outward movement thereof during rotor rotation two highly conductive mantle structures each having an inner surface and an outer surface, said mantle structures being disposed about each of the retaining ring structures such that said inner surface is in intimate electrical contact with said retaining ring, and means for electrically connecting said mantle structure to said rotor surface, said electrical connecting means providing an electrical path separate from said retaining ring structure.

2. A machine as claimed in claim 1, in which said electrical connection means comprising a plurality of electrically conductive wedges receivable in said slots for retaining said longitudinal conductor portions within said slots, each of said wedges having an extension which protrudes radially outward, said extension having a

radially outer surface which is contactable with said mantle structure.

3. A machine as claimed in claim 2 wherein said extensions' radially outer surface constitutes a highly
5 electrically conductive material which is softer than said wedges and said mantle.

4. A machine as claimed in claims 2 or 3 wherein said extensions' radially outer surface is contactable with a portion of the mantle's inner surface.

10 5. A machine as claimed in claim 4 wherein contact between said wedge extension and said mantle constitutes an interference fit.

6. A machine as claimed in any one of claims 1 to 5 wherein each of said mantle structures includes a
15 radially inward protrusion at the outboard axial ends of each retaining ring structure with each mantle structure's protrusion being in intimate electrical contact with said associated retaining ring's outboard axial end.


7. A machine as claimed in any one of claims 1 to 6 including a cylindrical support member disposable
20 about each of said mantle structures and in intimate contact with said mantle's outer surface, said support member providing radial retention of said mantle structure during rotor rotation.

25 8. A machine as claimed in claim 7 wherein each of said support members constitutes conductive material and has a radial thickness which is less than one depth of electrical current penetration for electrical current induced on the rotor surface.

30 9. A machine as claimed in any one of claims 1 to 8 wherein each of said mantle structures have a thickness between said inner and outer surfaces of at least one half depth of electrical current penetration for electrical current induced on the rotor surface.

35 10. A dynamoelectric machine, constructed and adapted for use, substantially as hereinbefore described and illustrated with reference to the accompanying drawings.








FIG. 3




FIG. 4



European Patent
Office

EUROPEAN SEARCH REPORT

0025292

Application number

EP 80 30 2849

| DOCUMENTS CONSIDERED TO BE RELEVANT | | | CLASSIFICATION OF THE APPLICATION (Int. Cl.) |
|---|---|----------------------------------|--|
| Category | Citation of document with indication, where appropriate, of relevant passages | Relevant to claim | |
| | <p><u>DE - C - 523 499</u> (AEG)</p> <p>* Page 2, right-hand column, line 57 - line 79 *</p> <p>--</p> <p><u>US - A - 4 123 676</u> (COOPER)</p> <p>* Column 3, line 57 - column 4, line 4; column 4, lines 17-65 *</p> <p>--</p> | <p>1</p> <p>1,7</p> | <p>H 02 K 3/51</p> |
| A | <p><u>FR - A - 2 236 300</u> (BBC)</p> <p>* Page 2, lines 8-14; page 4, lines 3-12 *</p> <p>--</p> | | <p>TECHNICAL FIELDS SEARCHED (Int. Cl.)</p> <p>H 02 K 3/51</p> |
| A | <p><u>BE - A - 559 451</u> (WESTINGHOUSE)</p> <p>* Page 9, line 32 - page 10, line 12 *</p> <p>--</p> | | |
| A | <p><u>FR - A - 1 153 058</u> (THOMSON-HOUSTON)</p> <p>* Page 3, left-hand column, lines 9-36 *</p> <p>--</p> | | |
| A | <p><u>GB - A - 1 281 348</u> (HARRISON-BUCHI)</p> <p>* Page 1, right-hand column, line 93 - page 2, left-hand column, line 26; page 3, left-hand column, lines 24-30 *</p> <p>----</p> | | <p>CATEGORY OF CITED DOCUMENTS</p> <p>X: particularly relevant</p> <p>A: technological background</p> <p>O: non-written disclosure</p> <p>P: intermediate document</p> <p>T: theory or principle underlying the invention</p> <p>E: conflicting application</p> <p>D: document cited in the application</p> <p>L: citation for other reasons</p> |
| <p>6 The present search report has been drawn up for all claims</p> | | | <p>&: member of the same patent family, corresponding document</p> |
| Place of search | | Date of completion of the search | Examiner |
| The Hague | | 20- 11-1980 | TANGOCCI |

EPO Form 1503.1 08.78

BAD ORIGINAL

